

PlusGuard 8 Series: 10 AMPS

The PlusGuard 8-10A is a multi-outlet design Voltage Protector rated at 10 Amps, prevents damages to electrical and electronic equipment from power fluctuation, especially over and under voltage levels of long duration. The 6 sec / 180 sec delay reconnection provides protection against power-back surge commonly experienced after resumption of power in a power cut situation. Build-in MOV excess electricity for additional protection. The PlusGuard 8-10A will automatically guard your equipment against brownouts or transient spikes induced by lighting or power line failure.



- > Delay Reconnection Selector 6 sec. / 180 sec.
- > Microprocessor Controlled Design
- > Surge Suppression 900 Joules
- > Grounded Multi-outlet Design
- > Provide Overload Protection
- > Wall Mountable

Specifications:

MODEL	PlusGuard 8-10A
INPUT	
Max. Current	10 Amps
Nominal Voltage	220-240Vac
Frequency	50Hz or 60Hz
Input Line Low Loss (@220Vac)	180Vac
Input Line Low Comeback (@220Vac)	190Vac
Input Line High Loss (@220Vac)	268Vac
Input Line High Comeback (@220Vac)	260Vac
Spike Protection	900 Joules
Connectors	Nema5-15P
OUTPUT	
Nominal Voltage	220-240Vac
Frequency	50Hz or 60Hz
Delay Timer	6 sec. / 180 sec.
Connectors	EURO-US socket*4pcs
INDICATOR	
LED	3 LEDs
ENVIRONMENT	
Operating Temperature	0°C-40°C (32°F-104°F)
Humidity	0-95% (Non-condensing)
Acoustic Noise	<40dB at 1M

*Product specifications are subject to change without further notice.