

PlusGuard 10 Series: 15 AMPS

The PlusGuard 10-15A is a multi-outlet design Voltage Protector rated at 15 Amps, prevents damages to electrical and electronic equipment from power fluctuation, especially over and under voltage levels of long duration. The 6 sec / 180 sec delay reconnection provides protection against power-back surge commonly experienced after resumption of power in a power cut situation. Build-in MOV excess electricity for additional protection. The PlusGuard 10-15A will automatically guard your equipment against brownouts or transient spikes induced by lighting or power line failure.



- > High voltage and low voltage cut-off protection
- > Delay reconnection selector 6 sec. / 180 sec.
- > LED indicators provide status information
- > Absorbs excess electricity through MOVs
- > Microprocessor controlled design
- > Surge suppression 900 Joules
- > Grounded multi-outlet design
- > Provide overload protection
- > Wall Mountable

Specifications:

MODEL	PlusGuard 10-15A
INPUT	
Max. Current	15 Amps
Nominal Voltage	220-240Vac
Frequency	50Hz or 60Hz
Input Line Low Loss (@220Vac)	180Vac
Input Line Low Comeback (@220Vac)	190Vac
Input Line High Loss (@220Vac)	268Vac
Input Line High Comeback (@220Vac)	260Vac
Spike Protection	900 Joules
Connectors	Nema 5-15P
Cable Length	1.8M (5.9ft)
OUTPUT	
Nominal Voltage	220-240Vac
Frequency	50Hz or 60Hz
Delay Timer	6 sec. / 180 sec.
Connectors	Universal Nema*7pcs
INDICATOR	
LED	3 LEDs
ENVIRONMENT	
Operating Temperature	0°C-40°C (32°F-104°F)
Humidity	0-95% (Non-condensing)
Acoustic Noise	<40dB at 1M
PHYSICAL	
Dimensions	320*50*32mm

*Product specifications are subject to change without further notice.