

## PlusCharger 1 Series

The PlusCharger 1-15A-18M is a Smart Charger Station rated at 15 Amps, it provides overload protection through power switch with built-in resettable circuit breaker. Built in MOV excess electricity for additional protection. It also equipped with smart charging station, SC-5VDC, USB charging port for smart devices power charging. The PlusCharger 1-15A-18M can ensure electrical safety and also provide power for devices with cables that can't reach any nearby electrical outlets.



- > Absorbs Excess Electricity through MOVs
- > Power Switch with Resettable Circuit Breaker
- > Fire Retardant Plastic Material
- > Provide Lightning, Surge, Overload Protection
- > Surge Suppression 900 Joules
- > Smart Charging Station 5VDC USB Charging Port
- > Grounded Multi-outlet Design
- > Wall Mountable

### Specifications:

MODEL	PlusCharger 1-15A-18M
<b>INPUT</b>	
Voltage Range	110 - 240Vac
Frequency	50Hz or 60Hz
Type of Input	NEMA 5-15P plug
Cable Length	1.8M (5.9ft)
<b>OUTPUT</b>	
Power Rating	15A
Type of Output: NEMA 5-15R	6 receptacles
USB Charging Port	5VDC, 4 ports, 3.4A Max.
<b>PROTECTION</b>	
Surge Rating	900 Joules
Overload Protection	Yes
Power Safety Shutdown	Yes
<b>PHYSICAL</b>	
Dimensions	320*50*32mm

\*Product specifications are subject to change without further notice.